

**AMENDMENTS TO CLAIMS:**

The listing of claims will replace all prior versions, and listings, of claims in the application:

**LISTING OF CLAIMS:**

1. (Original) A display driver apparatus for driving a display comprising a plurality of pixels, each of which is located at a respective one of a plurality of intersections formed between one of a plurality of common electrodes and one of a plurality of segment electrodes, wherein an orientation state of an electro-optical material of each pixel is controlled by a voltage applied to it, the display driver apparatus comprising:

a common electrode drive device that supplies a scanning signal for simultaneously selecting  $L$  common electrodes, where  $L$  is a natural number and  $L \geq 2$ ;

a segment electrode drive device that supplies a data signal to each of the plurality of segment electrodes;

a storage medium from which  $N$ -bit display data are simultaneously read out for each of the plurality of segment electrodes; and

a decoder having a plurality of sub-decoders and that divides the  $N$ -bit display data simultaneously read out from the storage medium into  $(N/L)$ -bit data units, decodes the  $(N/L)$ -bit data units, and outputs a voltage to be applied to each of the segment electrodes;

wherein

in a first mode, the  $N$ -bit display data provides  $2^A$  display gradients for each of  $L$  pixels on each of the segment electrodes, where  $A = (N/L) \geq 2$ , and an output voltage is output from a selected one of the sub-decoders in each of  $A$  divided periods of one horizontal scanning period, and

in a second mode, the  $N$ -bit display data provides  $2^B$  display gradients for each of  $n \times L$  pixels on each of the segment electrodes, where  $1 \leq B = A/n$  and  $n \geq 2$ , and an output voltage is output from a selected one of the sub-decoders every  $n$  horizontal scanning periods.

2. (Original) A display driver apparatus according to claim 1, further comprising a terminal that selects one of the first mode and the second mode.
3. (Original) A display driver apparatus according to claim 1, further comprising an interface circuit for inputting the N-bit display data from an external source, wherein a mode selection signal for selecting one of the first mode and the second mode is input through the interface circuit.
4. (Original) A display driver apparatus according to claim 1, wherein in the first mode the N-bit display data provides four display gradients for each of L pixels on each of the segment electrodes.
5. (Original) A display driver apparatus according to claim 4, wherein in the second mode the N-bit display data provides two display gradients for each of 2L pixels on each of the segment electrodes.
6. (Original) An electro-optical device comprising a display driver apparatus according to claim 1.
7. (Original) An electronic device comprising an electro-optical device according to claim 6.
8. (Original) A method for driving a display comprising a plurality of pixels, each of which is located at a respective one of a plurality of intersections formed between one of a plurality of common electrodes and one of a plurality of segment electrodes, wherein an orientation state of an electro-optical material of each pixel is controlled by a voltage applied to it, the display driving method comprising the steps of:
  - a common electrode drive device that supplies a scanning signal for simultaneously selecting L common electrodes, where L is a natural number and  $L \geq 2$ ;
  - supplying a data signal to each of the plurality of segment electrodes;
  - simultaneously reading N-bit display data for each of the plurality of segment electrodes; and

dividing each read N-bit display data into (N/L)-bit units, decoding the (N/L)-bit data units, and output a voltage to be applied to each of the segment electrodes;

wherein

in a first mode, the N-bit display data provides  $2^A$  display gradients for each of L pixels on each of the segment electrodes, where  $A = (N/L) \geq 2$ , and an output voltage is output in each of A divided periods of one horizontal scanning period, and

in a second mode, the N-bit display data provides  $2^B$  display gradients for each of  $n \times L$  pixels on each of the segment electrodes, where  $1 \leq B = A/n$  and  $n \geq 2$ , and an output voltage is output every n horizontal scanning periods.

9. (Original) A display driving method according to claim 8, further comprising the steps of inputting the N-bit display data from an external source, and inputting a mode selection signal for selecting one of the first mode and the second mode from an external source.

10. (Original) A display driving method according to claim 8, wherein in the first mode the N-bit display data provides four display gradients for each of L pixels on each of the segment electrodes.

11. (Original) A display driving method according to claim 10, wherein in the second mode the N-bit display data provides two display gradients for each of 2L pixels on each of the segment electrodes.